Yi Camera USB GUIDE

File list

📳 gui de. pptx	2015/7/30 19:27	Microsoft Powe	41 KB
🐸 setup. exe	2015/7/29 18:14	应用程序	19,032 KB
TDXJv22_1.2.6_build=20150709090932_b1031_i841_s1038.elf	2015/7/9 9:26	ELF 文件	45,156 KB
TDXJv22L_1.2.6_build=20150709094743_b1031_i841_s1038.elf	2015/7/9 9:55	ELF 文件	45,156 KB

1. setup.exe

update tool

2. YDXJ**.elf

firmware file

note:

Check your camera SN at the battery compartment Z2215** matches YDXJV22_1.2.6**.elf Z22L5** matches YDXJV22L_1.2.6**.elf

Installing and Updating

- 1. Double click on "setup.exe" and Install the USB tool
- 2. It's named as "yiSportCamUSB"



Preparing the Hardware:

- 1. Dismantle the front panel of the camera
- 2. Connect the camera USB to PC with a micro USB cable
- 3. Use tweezers to short-circuit in two points
 > One point above the Resistor
 > One point at GND
- 4. Press the power button and turn on the camera

Preparing the Hardware: image



Open yiSportCamUSB

yiSport	C an USB				
				Connect	DownLoad
ELF Prog	gramming —				1
C Firmw	are Progra	mming 🗌 Veri	fy		
				*	Choose
					-
Status:	Idle	Time: 00:00	Level: ER	ROR	Clear
					<u>A</u>

- 1. Check "Firmware Programming" radio button
- 2. Click on "Connect" button
- 3. If the short-circuit is successful, yiSportCamUSB will prompt "Found 1 YDXJ device!"

yiSportCamUSB				
		<	Connect	DownLoad
ELF Programming				
🖲 Firmware Prog	ramming 🔽 Ver	ify		
l.			_	Choose
Status: OK	Time: 00:00	Level: ERROR		Clear
'ound 1 YDXJ devi	ce!			
4				Þ

4. Click on "Choose" button and choose the option YDXJV22_1.2.6**.elf



5. Click on "Download" button and update the firmware The status label will show "OK", the text will show "Done!!" and the camera will beep 3 times later.

Now, the upgrade is complete.

Con Programming Firmware Programming Verify Users\antsOl\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-3 tus: Time: 00:05 Level: ERROR d 1 YDXJ device! d 1 YDXJ device! sers\antsOl\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-20 Done!	nect <u>D</u> ownLoad
Frogramming Firmware Programming Verify Users\antsOl\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-3 tus: Time: 00:05 Level: ERROR d 1 YDXJ device! d 1 YDXJ device! sers\antsOl\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-20 Done!	Clear
Firmware Programming Users\antsO1\Desktop\usbd1\YDXJv22_1.2.7-usbd1_build-3 tus: tus: Time: 00:05 Level: ERROR d 1 YDXJ device! d 1 YDXJ device! sers\antsO1\Desktop\usbd1\YDXJv22_1.2.7-usbd1_build-20 Done!	2015 V Choose
Users\antsO1\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build- tus: Time: 00:05 Level: ERROR d 1 YDXJ device! d 1 YDXJ device! sers\antsO1\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-20 Done!	2015 Choose
tus: Time: 00:05 Level: ERROR d 1 YDXJ device! d 1 YDXJ device! sers\antsO1\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build=20 Done!	Clear
d 1 YDXJ device! d 1 YDXJ device! sers\antsO1\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build=20 Done!]	
d 1 IDXJ device! sers\antsO1\Desktop\usbdl\YDXJv22_1.2.7-usbdl_build-20 Done!)	
DOUG	0150723120827_b103
	•