



Picasso M- User Debug mode Flash ROM Procedure (only for non-fused device)

- SOP v1.2

Date: 2012/5/30

Author: Eddy Chuang

Preparation:

1. Download the specific image pack and Picasso M USB driver to local disk.
2. Unzip the image pack and USB driver to C:/
3. Make sure of tablet device had full charging before ROM flashing.

ROM flash procedure:

1. Enter to Flash mode

- a) Turn power off on tablet device.
- b) Pressing and holding Volume up + down key simultaneously
- c) To stick the RESET button and let device enters to flashing mode.
- d) Release Volume Up/Down keys.

2. USB driver installation (only for first time of connecting)

- a) Connected PC and device via USB cable.
- b) PC will auto-detect the device and ask to install USB driver.
- c) On PC installing wizard, to select manual installing mode, then to indicate where of the driver (unzipped driver folder in C://) and finish the driver installation.
- d) Keeping on connection condition (PC – Tablet).

ROM flash procedure (cont.):

3. ROM flash

- a) Unzip ROM files [nvflash_Acer_AV041_A510_RV28RC03_EMEA_GB(Debug for non-fused device).7z] to C://
- b) To make sure of the following files in folder
 1. => flash.bct
 2. => flash.cfg
 3. => bootloader.bin
 4. => boot.img
 5. => system.img
 6. => recovery.img
 7. (=> userdata.img)
 8. (=> flexrom.img)
- c) Double click "!Flash.bat " and pc will pop-up DOS command mode window.
- d) Flash start.... (Success case will show the flashing process on pc)
- e) **!!Failed Case!!** If you did not see any processing on command mode at start, please repeat again **1. Enter to Flash mode** and connecting PC, and then **3. ROM flash**.

acer

Thank you